



Features	WT11	WT12	WT32	WT21	WT41
<b>Bluetooth specification</b>	2.0 + EDR, 2.1 + EDR	2.0 + EDR, 2.1 + EDR	2.1 + EDR	2.1 + EDR	2.1 + EDR
<b>Bluetooth class</b>	1	2	2	1	1
<b>Range, line of sight</b>	250m	40m	40m (80m WT32-E)	120m	1000m
<b>Antenna</b>	Internal or U.FL	Internal, PIN	Internal, W.FL, PIN	Internal, PIN	Internal, PIN
<b>Temperature range</b>	-40° to +85°	-40° to +85°	-30° to +85°	-40° to +85°	-40° to +85°
<b>Maximum throughput</b>	2,1Mbps	2,1Mbps	2,1Mbps	2,1Mbps	2,1Mbps
<b>Integration</b>	Surface mount	Surface mount	Surface mount	Surface mount	Surface mount
<b>Host interfaces</b>	UART, USB, 6xGPIO,1xAIO	UART, USB, 6xGPIO	UART, USB, 10xGPIO, 2xAIO	UART, CSPI, SDIO, 7xGPIO	UART, USB, 6xGPIO, 1xAIO
<b>Audio interfaces</b>	PCM	PCM	Analog, PCM, SPDIF, I2S	I <sup>2</sup> S + PCM	PCM
<b>Operating voltage</b>	3.0V- 3.6V	2.7V- 3.6V	2.5V- 4.4V	1.8V or 2.7V- 4.9V	3.0V- 3.6V
<b>AFH supported</b>	Yes	Yes	Yes	Yes	Yes
<b>802.11 co-existence</b>	Yes	Yes	Yes	Yes	Yes
<b>Memory</b>	48KB RAM, 8MB Flash	48KB RAM, 8MB Flash	48KB RAM, 8MB Flash	ROM	48KB RAM, 8MB Flash
<b>Chip</b>	BlueCore-04	BlueCore-04	BlueCore-05 Multimedia	BlueCore-06	BlueCore-04
<b>Supports Bluelab SDK</b>	Yes	Yes	Yes	No	Yes
<b>Certifications</b>	Bluetooth, CE, FCC, IC, TELEC and MK	Bluetooth, CE, FCC, IC and TELEC	Bluetooth, CE, FCC and IC	Bluetooth, CE, FCC and IC	Bluetooth, CE, FCC, IC, TELEC and MK
<b>Ability to host applications</b>	Yes	Yes	Yes	No	Yes
<b>Firmware options</b>	iWRAP, HCI, Custom	iWRAP, HCI, Custom	iWRAP, Custom	HCI	iWRAP, HCI, Custom
<b>Size</b>	35 x 14 x 2,3mm	26 x 14 x 2,4mm	24 x 16 x 0,3mm	17,1 x 11,6 x 2,6mm	35 x 14 x 3,5mm
<b>Profiles</b>	SPP, DUN, HFP, HSP, HID, AVRCP, DI, PBAP, OPP, FTP, HDP	SPP, DUN, HFP, HSP, HID, AVRCP, DI, PBAP, OPP, FTP, HDP	SPP, DUN, HFP, HSP, HID, AVRCP, DI, PBAP, OPP, FTP, HDP, A2DP	HCI over UART, CSPI, SDIO	SPP, DUN, HFP, HSP, HID, AVRCP, DI, PBAP, OPP, FTP, HDP



Features	<b>AS 2291/2293</b>	<b>AP3201</b>	<b>AP3241</b>
<b>Bluetooth specification</b>	2.0/2.1 + EDR	2.0/2.1 + EDR	2.1 + EDR
<b>Bluetooth class</b>	1 (Configurable for Class 2)	1 (Configurable for Class 2)	1
<b>Range, line of sight</b>	200m	200m	1000m
<b>Number of connections</b>	Up to 21	Up to 7	Up to 7
<b>Antenna</b>	Internal or external	Internal or external	Internal
<b>Temperature range</b>	0° to +60°	0° to +60°	0° to +60°
<b>Maximum throughput</b>	2,1Mbps	2,1Mbps	2,1Mbps
<b>Integration</b>	Housed or OEM in PCB form	Housed or OEM in PCB form	Housed or OEM in PCB form
<b>Interfaces</b>	ETH, CF, USB, RS-232, 14GPIO	ETH, USB	Ethernet, USB host
<b>DC input</b>	9-24 VDC	9-24 VDC	9-24 VDC
<b>AFH supported</b>	Yes	Yes	Yes
<b>Network management</b>	BSM, web interface, SSH	BSM, web interface, SSH	BSM, web interface, SSH
<b>Memory*)</b>	32MB RAM, 32MB Flash	32MB RAM, 16MB Flash	32MB RAM, 16MB Flash
<b>Bluetooth module</b>	Bluegiga WT11-A/E	Bluegiga WT11-A/E	Bluegiga WT41
<b>Certifications</b>	Bluetooth, CE, FCC and IC	Bluetooth, CE, FCC and IC	Bluetooth, CE, FCC, IC and Telec
<b>Ability to host applications</b>	Yes	Yes	Yes
<b>Operating system</b>	Linux	Linux	Linux
<b>Weight</b>	364 g	74 g	74 g
<b>Size</b>	220x150x30mm	90x59x30mm	90x59x30mm
<b>Profiles</b>	SPP, OBEX OPP, OBEX FTP, PAN, LAN Access, DI, HDP	SPP, OBEX OPP, OBEX FTP, PAN, LAN Access, DI, HDP	SPP, OBEX OPP and FTP, PAN, LAN Access, DI and HDP

\*) Extendable to GBs

### Bluegiga Solution Manager (BSM)

Bluegiga Solution Manager (BSM) is a web-based remote management and monitoring platform for Bluegiga Access Servers. By using BSM, you can simultaneously upgrade, monitor and configure a large number of Bluegiga Access Servers, instead of configuring each device one-by-one.

- ▶ Provides remote management of Bluegiga Access Servers
- ▶ Enables managing the *Bluetooth* marketing applications (ObexSender)
- ▶ Simple graphical user interface
- ▶ Can be used over LAN, GPRS, or any other Internet connection type
- ▶ Communicates by using secure, encrypted network protocols
- ▶ Works seamlessly through firewalls
- ▶ Enables remote upgrades of Bluegiga Access Server software and content
- ▶ Available APIs enable complete look and feel customization
- ▶ User permissions can be tailored to provide different levels of user accounts

[www.bluegiga.com](http://www.bluegiga.com)